



Surface Mount Schottky Rectifier

Features

- Low profile package
- Ideal for automated placement
- Guardring for overvoltage protection
- Low power losses, high efficiency
- High forward surge capability
- Meets MSL level 1, per J-STD-020, LF maximum peak of 260 °C
- Part no. with suffix "Q" means AEC-Q101 qualified

Typical Applications


For use in low voltage high frequency inverters, freewheeling, DC/DC converters, automotive and polarity protection applications.

Mechanical Data

- **Package:** DO-214AA (SMB)

Molding compound meets UL 94 V-0 flap ' Ů ' ' Ů

PM



Repetitive peak reverse voltage	V_{RRM}	V	150	200
Maximum RMS voltage	V_{RMS}	V	105	140
Maximum DC blocking voltage	V_{DC}	V	150	200
Maximum average forward rectified current at T_L (Fig.1)	I_O	A	2.0	
Surge(non-repetitive)forward current @60Hz half-sine wave,1 cycle, $T_J=25$	I_{FSM}	A	75	
Voltage rate of change (rated V_R)	dV/dt	V/ μ s	10000	
Storage temperature	T_{stg}		-55 ~+175	
Junction temperature	T_J		-55 ~+175	

■Electrical Characteristics($T_a=25$ Unless otherwise specified)

PARAMETER	SYMBOL	TEST CONDITIONS		TYP	MAX	UNIT
Instantaneous forward voltage	V_F	$I_F=2A$	$T_J=25$	0.82	0.9	V
			$T_J=125$	-	0.75	
Reverse current	I_R	Rated V_R	$T_J=25$	-	5	μ A
			$T_J=125$	15	150	
Typical junction capacitance	C_J	$V_R=4V, f=1MHz$		40	-	pF



SS215Q THRU SS220Q

Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with automotive electronics, are not designed for use in medical, lifesaving, lifesustaining, or military, Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's s