




MD75S-M4

Applications

- Three phase rectifiers for power supplies
- Rectifiers for DC motor field supplies
- Battery charger rectifiers
- Input rectifiers for variable frequency drives

Features

- Three phase bridge rectifier
- Blocking voltage:800 to 1800V
- Heat transfer through aluminum oxide DBC ceramic isolated metal baseplate
- Glass passivated chip
- UL recognized applied for file no. E230084



--	--	--

Maximum Ratings

Symbol	Conditions	Values	Units
ID	Three phase, full wave Tc=110	75	A
IFSM	t=10mS Tvj =45	1020	A
i ² t	t=10mS Tvj =45	5500	A ² s
Visol	a.c.50HZ;r.m.s.;1min	3000	V
Tvj		-40 to +150	
Tstg		-40 to +125	
Mt	To terminals(M5)	3±15%	Nm
Ms	To heatsink(M5)	3±15%Rth(j-c)	Per diode /W

ID	Rth(j-c) 75 A	Per Module	0.183 VRRM 800 to 1800V



